



ACTIVATION INSTRUCTIONS

Pairing with every device equipped with Bluetooth™, device control panel will manage volume and functions.

TECHNICAL FEATURES

- Bluetooth Audio Receiver Board, version 4.0
- Class D amplifier - 50 W x 2
- Primary power supply 100-240 V
- Secondary power supply 24 V 5 A

AMPLIFIER

Loading	- reflex
Channels	- 2
Nominal Power (W)	- 65
X-over (Hz)	- 2,5 k
Frequency Response(Hz)	- 45-21 k
Sensitivity (db)	- 89
Speakers	- No. 1 coaxial D. 160 mm with phase compensator

SPEAKERS

Manufacturer	- laboratorioaudio.it
Type	- coaxial
Loading	- pneumatic
Channels	- 1
RMS Power (W)	- 50
MAX Power (W)	- 75
Impedance (ohm)	- 8
X-over (Hz)	- 4,5 k
Frequency Response (Hz)	- 50-19 k
Sensitivity(db)	- 89
Ways	- n° 1 midwoofer D. 160 mm - n° 1 tweeter D. 13 mm MYLAR neodymium
Dimensions WxHxT (cm)	- 100 x 90 x 55
Weight (Kg)	- 60
Notes	- *wood cabinet